



VENUS CONTROL SUITE

TRANSFERRING CONTENT FROM VENUS 1500 V4 TO VENUS CONTROL SUITE

A step by step process on how to move content from Venus 1500 V4 to your new Venus Control Suite Software.

TRANSFERRING CONTENT



1. Open Venus 1500 V4 by clicking on the **Orange V** .
2. If a display is not selected, select a display from the center dropdown.
3. Click the **Content** tab.
4. Click the **Create Button** to open Content Studio.
5. Click the **Application Menu** (Orange V) in the upper left corner and select **Open**.
6. Choose the preferred display and click **next** (users may only have one option).
7. Select content file and click **Open**.
8. Once the presentation is open, click the **Application Menu** (Orange V) in the upper left corner and select **Save As**.
9. Under **Systems**, choose the external location (i.e. Desktop, My Documents, My Computer, My Network) to save your message (see figure 1).
10. Name your content in the **File Name field** at the bottom (leave the file type as VMPF files).
11. Click **Save**.
12. Repeat steps 5-11 for all content that needs to be transferred.
13. To upload saved content into Venus Control Suite, navigate and log into <https://venus.daktronics.com>.
14. Click the **Media** icon .
15. Click **Upload**.
16. Click **Drop files or click here to upload** in the Upload Media box and navigate to your saved VMPF files (see figure 2).
17. Select VMPF file(s) and click **Open**.
18. Once the files have finished uploading, you may tag them or click **Finish** (see figure 2).

✓ **Tip:** Choose multiple files by holding the ctrl key down on your keyboard as you select multiple files.




Figure 1: Select location from the System




Figure 2: Uploading VMPF Files